

Stable · Durable · Performance GF8100 M2 + SE

Better than ever

CD-IN Connector

- *CD-IN-Anschluss
- *Connecteur d'entrée CD
- *Connettore CD-in
- *Conector de entrada de CD
- *Conector para entrada de CDs
- *Złącze wejścia CD
- *Разъём ввода для CD
- *CD-インコネクタ
- *مفخذ CD-IN

4	1
2	2
3	3
1	4

1 Left Channel Input
2 Ground
3 Ground
4 Right Channel Input

S/PDIF-OUT Connector

- *S/PDIF-Ausgangsanschluss
- *Connecteur de sortie S/PDIF
- *Connettore output SPDIF
- *Conector de salida S/PDIF
- *Conector de saída S/PDIF
- *Złącze wyjścia S/PDIF
- *Разъём вывода для S/PDIF
- *S/PDIFアウトコネクタ
- *مفخذ خرج S/PDIF

3	1
2	2
1	3

1 +5V
2 SPDIF_OUT
3 Ground

5.1-Channels HD Audio

- *Unterstützt High-Definition Audio / 5.1-Kanal-Audioausgabe
- *Prise en charge de l'audio haute définition / Sortie audio à 5.1 voies
- *Supporto audio High-Definition (HD) / Uscita audio 5.1 canali
- *Soporte de sonido de Alta Definición / Salida de sonido de 5.1 canales
- *Suporta a especificação High-Definition Audio / Saída de áudio de 5.1 canais
- *Obsługa High-Definition Audio / 5.1 kanałowe wyjście audio
- *Звуковая поддержка High-Definition / 5.1канальный звуковой выход
- *ハイデフィニションオーディオのサポート / 5.1チャンネルオーディオアウト
- *تدعم تقنية الصوت عالي التعريف / 5.1 قنوات لخرج الصوت

Front Audio Connector

- *Front-Audioanschluss
- *Connecteur Audio du panneau avant
- *Connettore audio frontale
- *Conector de sonido frontal
- *Conector de áudio frontal
- *Przednie złącze audio
- *Входной звуковой разъём
- *フロントオーディオコネクタ
- *مفخذ الصوت الأمامي

1	2
3	4
5	6
7	8
9	10

1 Mic Left in
2 Mic Right in
3 GPIO
4 Right line in
5 Jack Sense
6 Front Sense
7 Front Sense
8 Key
9 Left line in
10 Jack Sense

Printer Port Connector

- *Druckeranschluss Anschluss
- *Connecteur de Port d'imprimante
- *Connettore Porta stampante
- *Conector Puerto de impresora
- *Разъём Порт подключения принтера
- *مفخذ طابعة

Serial Port Connector

- *Serieller Anschluss
- *Connecteur de Port série
- *Connettore Porta serie
- *Conector Puerto serie
- *Разъём Последовательный порт
- *مفخذ تسلسلي

Floppy Disk Drive Connector


- *Diskettenlaufwerkanschluss
- *Connecteur de disquette
- *Connettore floppy
- *Conector disco flexible
- *Разъём Дискета
- *مفخذ محرك أقراص مرنة

System Fan Header

- *System-Lüfter-Sockel
- *Embase de ventilateur système
- *Collettore ventolina sistema
- *Cabecera de ventilador de sistema
- *Conector da ventoinha do sistema
- *Złącze główkowe wentylatora systemowego
- *Контактирующее приспособление вентилятора системы
- *システムファンヘッダ
- *وصلة مروحة النظام

3	1
2	2
1	3

1 Ground
2 +12V
3 FAN RPM rate sense



Back Panel I/O Connectors

- *Rückseiten-E/A
- *E/S du panneau arrière
- *I/O pannello posteriore
- *Panel trasero de E/S
- *مفخذ ديل الخلفية
- *Entradas/Saídas no painel traseiro
- *Back Panel I/O
- *Задняя панель средств ввода-вывода
- *背面I/O

PS/2 Mouse
PS/2 Keyboard
VGA
DVI-D
USB2
USB2
10/100 Mbps LAN
Line In
Surround
Line Out
Mic In 1/1
Base Center

Power Connector (4pin)

- *Stromanschluss(4-polig)
- *Connecteur d'alimentation(4 broches)
- *Connettore alimentazione(4 pin)
- *Conector de alimentación(4 patillas)
- *Conector de alimentação(4 pinos)
- *Złącze zasilania (4 pinowe)
- *Разъём питания (4 вывода)
- *電源コネクタ(4ピン)
- *مفخذ توصيل الطاقة(4 دبوس)

2	1
3	4

1 +12V
2 +12V
3 Ground
4 Ground

NB Chipset : GeForce 8100

- *NB Chipsatz: GeForce 8100
- *NB Conjunto de chips: GeForce 8100
- *Набор микросхем: GeForce 8100
- *مجموعة الشرائح: GeForce 8100

Socket AM2+ for AMD Sempron / Athlon 64 FX / Athlon 64 X2 / Phenom Processor FSB: Up to 5.2GT/s Bandwidth

- *Socket AM2+
- *AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom Prozessoren
- *Socket AM2+
- *Processeurs AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom
- *Socket AM2+
- *Conector AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom
- *Conector AM2+
- *Processadores AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom
- *Socket AM2+
- *Processadores AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom
- *Socket AM2+
- *AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom Processor
- *Набор AM2+
- *Процессоры AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom
- *مفخذ AM2+
- *معالجات AMD Athlon 64/Athlon 64 FX/Athlon 64 X2/Sempron/Phenom

DDR2 DIMM Slots : Each DIMM supports 256MB/512MB/1GB/2GB/4GB DDR2 533/667/800 & 1066(by AM2+ CPU)

- *DDR2 DIMM-Steckplätze
- *Jeder DIMM unterstützt 256MB/512MB/1GB/2GB/4GB DDR2 533/667/800/1066
- *Fentes DDR2 DIMM
- *Chaque DIMM prend en charge des DDR2 533/667/800/1066 de 256Mo/512Mo/1Go/2Go/4Go
- *Alloggi DIMM DDR2
- *Ciasun DIMM supporta DDR2 533/667/800/1066 256MB/512MB/1GB/2GB/4GB
- *Ranuras DIMM DDR2
- *Cada DIMM admite DDR2 533/667/800/1066 de 256MB/512MB/1GB/2GB/4GB
- *Gniazda DDR2 DIMM
- *Każde gniazdo DIMM obsługuje moduły 256MB/512MB/1GB/2GB/4GB DDR2 533/667/800/1066
- *Слоты DDR2 DIMM
- *Каждый модуль DIMM поддерживает 256МБ/512МБ/1ГБ/2ГБ/4ГБ DDR2 533/667/800/1066
- *DDR2 DIMM スロット
- *各DIMMは 256MB/512MB/1GB/2GB/4GB DDR2 533/667/800/1066をサポート
- *مفخذ DDR2 DIMM
- *تدعم ذاكرة من نوع DIMM تدعم DDR2 533/667/800/1066 سعة 256 ميبايت و512 ميبايت و1 جيبايت و2 جيبايت و4 جيبايت

CPU Fan Header

- *CPU-Lüfter-Sockel
- *Embase de ventilateur UC
- *Collettore ventolina CPU
- *Cabecera de ventilador de CPU
- *Conector da ventoinha da CPU
- *Złącze główkowe wentylatora procesora
- *Контактирующее приспособление вентилятора центрального процессора
- *CPUファンヘッダ
- *وصلة مروحة وحدة المعالجة المركزية

4	1
2	2
3	3
1	4

1 Ground
2 +12V
3 FAN RPM rate sense
4 Smart Fan Control

PCI Slots

- *PCI-Steckplatz
- *Fente PCI
- *Alloggio PCI
- *Ranura PCI
- *Ranura PCI
- *Gniazdo PCI
- *Слот PCI
- *PCIスロット
- *مفخذ PCI

USB 2.0 Connectors

- *USB 2.0-Anschluss
- *Connecteur USB 2.0
- *Connettore USB 2.0
- *Conector USB 2.0
- *Conector USB 2.0
- *Złącze USB 2.0
- *Разъём USB 2.0
- *USB 2.0コネクタ
- *مفخذ USB 2.0

Front Panel Connector

- *Fronttafelanschluss
- *Connecteur du panneau avant
- *Connettore pannello frontale
- *Conector de panel frontal
- *Conector do painel frontal
- *Złącze panela przedniego
- *Разъём на лицевой панели
- *フロントパネルコネクタ
- *مفخذ اللوحة الأمامية

1	2	3	4	5	6	7	8	9	10
1	2	3	4	5	6	7	8	9	10

Speaker
HDD LED
Reset
Power LED
On/Off

PCI-Express Gen2 x16 Slot

- *PCI Express Gen2 x16-Steckplatz
- *Fente PCI Express Gen2 x16
- *Alloggio PCI Express Gen2 x16
- *Ranura PCI express Gen2 x16
- *Ranura PCI express Gen2 x16
- *Gniazdo PCI Express Gen2 x16
- *Слот PCI Express Gen2 x16
- *PCI Express Gen2 x16スロット
- *مفخذ PCI Express Gen2 x16

Clear CMOS Header

- *"CMOS löschen"-Sockel
- *"Embase d'effacement CMOS"
- *"Collettore cancellazione CMOS"
- *"Cabecera de borrado de CMOS"
- *"Conector para limpeza do CMOS"
- *"Złącze główkowe kasowania CMOS"
- *"Открытое контактирующее приспособление CMOS"
- *"CMOSクリアヘッダ"
- *وصلة مسح CMOS

1	2	3	4	5	6	7	8	9	10
1	2	3	4	5	6	7	8	9	10

Pin 1-2 Close: Normal Operation (default)
Pin 2-3 Close: Clear CMOS data

Power Connector (24pin)

- *Stromanschluss(24-polig)
- *Connecteur d'alimentation (24 pins)
- *Connettore alimentazione(24 pinos)
- *Conector de alimentação (24 pinos)
- *Złącze zasilania (24 pinowe)
- *Разъём питания (24 вывода)
- *電源コネクタ(24ピン)
- *مفخذ توصيل الطاقة(24 دبوس)

SATA Connectors

- *SATA-Anschluss
- *Connecteur SATA
- *Connettore SATA
- *Conector SATA
- *Conector SATA
- *Złącze SATA
- *Разъём SATA
- *SATAコネクタ
- *مفخذ SATA

IDE Connector


- *IDE-Anschluss
- *Connecteur IDE
- *Connettore IDE
- *Conector IDE
- *Conector IDE
- *Złącze IDE
- *Разъём IDE
- *IDEコネクタ
- *مفخذ IDE

The Motherboard Trusted by Media

www.tomshardware.com
RECOMMENDED BUY
NOVEMBER 2006
www.anandtech.com
REVIEWED


CHIP Editor's Choice
iXBT
HardOCP
PC Stats
Atomic
AuJa
Bjorn3D
BUG
CHIP PRESTIGE
CHIP No1
CHIP TOP Quality
CLUB OVERCLOCKER
CHIP TEST-WINNER 2006
Custom PC
Custom PC
CRW
CRW
DOSV Power Report
Guru3D
Hardware
HardwareZone
Igormania
Noticias 3D
Noticias 3D
N3D
OverclockerCafe
PC Achat
HardwareZone
PC Lab
PC Magazine
PC Modding
PC Modding
PC Professionale
PC Power Play
PC WORLD
PC WORLD
PC WORLD
PC WORLD
PC WORLD
TweakTown
3DItalia

Step 1:CPU Installation




AM2+ CPU Socket
Supports AMD Sempron / Athlon 64 / Athlon 64 FX / Athlon 64 X2 / Phenom
FSB: Supports up to 5.2GT/s Bandwidth

Step 1: Remove the protection cap from the CPU socket and keep the cap well.




⚠ CAUTION
Our RMA policy only accepts the mainboard comes with the cap on the CPU socket, so please keep the protection cap well after installation. We will not be responsible for any damage to the pin-leg of the CPU socket resulting from misplacement/loss/incorrect removal of the protection cap.


Step 2: Pull the socket locking lever out from the socket and then raise the lever up to a 90-degree angle.




Step 3: Look for the triangular cut edge on socket, and the golden dot on CPU should point forwards this triangular cut edge. The CPU will fit only in the correct orientation.




Step 4: Hold the CPU down firmly, and then lower the lever to locked the position.



Step 5: Place the heatsink and fan assembly onto the retention frame. Match the heatsink clip with the socket mounting-lug. Hook the spring clip to the mounting-lug.




Step 6: On the other side, push the retention clip straight down to lock into the plastic lug on the retention frame, and then press down the locker until it stops.




Note:
Do not forget to connect the CPU fan connector. For further information, please refer to **Step 3:Power Connection**.

Step 2:Memory Installation




DDR2 DIMM Slot x2
Supports DDR2 533/667/800
Supports DDR2 1066(by AM2+ CPU)
Each DIMM supports 256MB / 512MB / 1GB / 2GB / 4GB DDR2
Max Memory Capacity is 8GB

Step 1: Unlock a DIMM slot by pressing the retaining clips outward. Align a DIMM on the slot such that the notch on the DIMM matches the break on the Slot.




Step 2: Insert the DIMM vertically and firmly into the slot until the retaining chip snap back in place and the DIMM is properly seated.




Step 3:Power Connection

CPU Fan Power (JCFAN)
JCFAN supports 4-pin head connector. When connecting with wires onto connectors, please note that the black wire is Ground and should be connected to pin#1(Ground).




CPU Fan Power

24-pin ATX Power (JATXPWR1)
JATXPWR1 is the main power supply connector located along the edge of the board next to the CPU socket. Firmly plug the power supply cable into the connector and make sure it is secure.




24-pin ATX Power

4-pin ATX Power (JATXPWR2)
JATXPWR2, the 4-pin ATX 12V power connection, is used to provide power to the CPU. Align the pins to the connector and press firmly until seated.



4-pin ATX Power


Installation Complete
Follow the three steps to finish CPU, memory, and power installation, and the whole motherboard assembly should looks like this picture.



Clear CMOS Header

The Occasion to Clear CMOS

1. Forgot the supervisor/user password preset in the BIOS menu.
2. Unable to boot up the system because the CPU clock was incorrectly set in the BIOS menu.
3. The CMOS data becomes corrupted.



Clear CMOS Header (JCMOS)


1 Pin 1-2 Close: Normal Operation (default)

1 Pin 2-3 Close: Clear CMOS data


Clear CMOS Procedure

1. Remove AC power line.
2. Set the jumper to "Pin 2-3 close".
3. Wait for five seconds.
4. Set the jumper to "Pin 1-2 close".
5. Power on the AC.
6. Reset your desired password or clear the CMOS data.


NOTE: How to Setup Jumpers
The illustration shows how to set up jumpers. When the jumper cap is placed on pins, the jumper is "close", if not, that means the jumper is "open".



Pin Open




Pin Closed



Pin 1-2 Closed


Driver & Manual

After you installed your operating system, please insert the Fully Setup Driver CD into your optical drive and install the driver for better system performance. You will see following window after you insert the CD.



Click on **Driver** to start the process of driver installation.

The installation program will detect your system to find out the driver needed to be installed.




Click on **Install** and the program will begin to install the proper driver for your system.

When the driver installation completes, there will be a dialogue appears asking you to restart the system. Please click on **YES** to restart your computer.

For more information of the mainboard setup and BIOS setup, please refer to the full version manual in the setup CD.

In the Setup CD auto-run program, click on **Manual** and then click on **Mainboard User Manual** or **BIOS User Manual**.



Package Checklist

▲ Installation Guide x 1	▲ HDD Cable x 1
▲ Fully Setup Driver CD x 1 (full version manual files inside)	▲ Rear I/O Panel x 1
▲ Serial ATA Cable x 1	▲ FDD Cable x 1 (optional)
▲ Serial ATA Power Cable x 1 (optional)	▲ Parallel Printer Cable x1 (optional)

Note: The package contents may differ by area or your motherboard version.

Serial NO. Definition

N78VBM2S-xx 60xxxxxxx00001

PCB Version NO.

Serial NO. of Production

Manufacturer's Internal Part NO.

Q&A of Technical Support

Q: How to get a quick response for my request on technical support?
A: Please carry out a simple troubleshooting before sending "Technical Support Form" on our website.

Q: Is the motherboard dead? Do I need to return it to where I bought from or go through an RMA process?
A: After you had gone through the troubleshooting procedures, yet the problem still exists, or you find an evident damage on the motherboard. Please contact your reseller shop to get the RMA service.

Copyright and Warranty Notice

The information in this document is subject to change without notice and does not represent a commitment on part of the vendor, who assumes no liability or responsibility for any errors that may appear in this manual.

No warranty or representation, either expressed or implied, is made with respect to the quality, accuracy or fitness for any particular part of this document. In no event shall the manufacturer be liable for direct, indirect, special, incidental or consequential damages arising from any defect or error in this manual or product.

Product names appearing in this manual are for identification purpose only and trademarks and product names or brand names appearing in this document are the property of their respective owners.

This document contains materials protected under International Copyright Laws. All rights reserved. No part of this manual may be reproduced, transmitted or transcribed without the expressed written permission of the manufacturer and authors of this manual.

If you do not properly set the motherboard settings, causing the motherboard to malfunction or fail, we cannot guarantee any responsibility.

